




## Instructions For the Fastime 11 Stopwatch: countdown timer, alarm and time of day functions

### Stopwatch mode:

A	B	Event Timing:	Split Timing:	1-2 Finish:
		<b>D</b> – Start  <b>D</b> – Stop (time Out)  <b>D</b> – Continue  <b>D</b> – Stop  <b>C</b> - Reset	Press <b>B</b> anytime to switch between cumulative split and lap split  <b>D</b> –Start  <b>C</b> – Split  <b>C</b> - Release  <b>D</b> – Stop  <b>C</b> - Reset	<b>D</b> – Start  <b>C</b> – Stop  <b>D</b> – Stop (1 <sup>st</sup> finish time)  <b>C</b> – Release (2nd finish time)  <b>C</b> - Reset
C	D	E		

Press **A** button to move to Repeating Countdown Timer (9hr 59m 59sec) display:

Press **B** to select from three options:

CR = Repeating Countdown. CC = Countdown to zero then count up.

CS = Countdown then stop

To set timer, Press and hold **A** until digits flash. Press **B** to choose digits to change. Press **D** to change the digits. Press **A** to exit setting.

To start/stop the timer press **D**

Press **A** button to move to Time of Day/date display:

To set time of day and date, Press and hold **A** until digits flash. Press **B** to choose digits to change. Press **D** to change the digits. Press **A** to exit setting

Press **C** button to move to Alarm display:

To set alarm time, Press and hold **A** until digits flash. Press **B** to choose digits to change. Press **D** to change the digits. Press **A** to exit setting